FM880-EA-000





- 6 Channels Of Optocoupler Digital Signal Input, Three Of Which Support Wide Voltage Input (5~24VDC)
- 3 Light Coupling Digital Signal Lost Output
- All The Analog Input (Plus Or Minus 10v) Control Speed
- Support Double Pulse (The CW/CCW) Model (P/D), Pulse Direction And Incremental Encoder (AB) Mode Control
- 100MBps Ethernet Transceiver With Isolation
- Support EtherCAT Bus Protocol Control, Optimize Customer Control Circuit
- Has Rich IO Function Configuration, Support Origin And Multistage Speed Control Mode
- Support Motor Parameters Automatically To Adapt To, Custom Lock Shaft Current, Such As Micro Step Filtering Function
- Powerful Protection Function: Overvoltage, Undervoltage, Overheating And Over-Current Protection
- RS232 Serial Communication, The Use Of Upper Machine Software KincoStep Parameters Set

Rating: Not Rated Yet
Price
Sales price without tax 270,00 €

Ask a question about this product

ManufacturerMaker: Kinco

Description

Technical Specifications	
Model	**FM880-EA-000**
Supply Voltage	24VDC?70VDC
Over-voltage Protection	Above 85VDC
Under-voltage protection	Below 15VDC
Input Current	0.1?10A (Peak?
Subdivision	Upper Computer Software KincoStep Setting
Adaptive Motor	Two - phase 86 And Three - Phase

	57, 85 Hybrid Stepping Motors
Control Method	EtherCAT Bus Protocol Control, IO Control, Analog ControlPulse Control: Pulse + Direction (PLS+DIR, Positive And Negative Pulse (CW/CCW), A+B Phase
Cooling Method	Natural Air Cooling
Operating Environment	Avoid Large Amounts Of Metal Dust, Oil Mist Or Corrosive Gases
Operating Humidity	<85%, RH?No Dews Or Dewdrops)
Operating Temperature	0??+40?
Storage Temperature	-20??+70?
Weight	0.363Kg
Dimensions	134.5 x 75.5 x 34mm
Ingress Protection	IP20

FM880-EA-000 Dimensions

KincoCatalog Stepper