

ED430-0126-AA-K-000



- ?????????? ?????????? ??????????: RS-232, RS-485, CAN BUS, PROFIBUS DP.
- ??? AC220V±15%
- ?????????KW?: 0.1-1.57
- ??????????: 265X165X62 265X165X97

?????????: ?? ?????????????

Price

Sales price without tax 903,00 €

[?????? ?? ?? ??????](#)

Manufacturer [ELCON | Systems & Components](#)

Description	ED430-010XA-G-00	ED430-020XA-G-00	ED430-040XA-G-00	ED430-075XA-G-00	ED430-105XA-S-00	ED430-126XA-S-00	ED430-157XA-S-00
	Single-phase AC220V±15%				3-phase AC220V±15%		
	50Hz?60Hz						
	DC24±10% , 2A						
	DC24±10%, 10mA						

Digit al signal output	DC24±10%, 0.5A						
Anal og signal input	-10V~+10V						
Rate d loa d?K W?	0.1	0.2	0.4	0.75	1.05	1.26	1.57
Ener gy-c onsu med braki ng	If the system generates an over-voltage alarm when it starts or stops sharply, add an external braking resistor to absorb the feedback energy of the motor, the minimum resistance for ED430 series is 27?						
Ener gy-c onsu med braki ng v oltag e	DC385±5V						
Over- volta ge al arm volta ge	DC400±5V						
Unde r-volt age al arm volta ge	DC210±5V						
Dime nsio ns mm (H×W ×D)	265X165X62			265X165X97			
Working environment							
Weig ht	1.9Kg			3Kg			
Oper ating temp eratu re	0~40?						
Stora ge te mper ature	-10~70?						
Humi dity	5~85%						
Cont amin ation level	2						
Prote ction level	IP20						
Instal latio n env	Installed in a dust-free, dry, and lockable environment (in a electrical cabinet, for example)						

iron ment	
Installation mode	Vertical installation
Installation altitude	No power limit under 1000m
Pressure	86?106kpa
General functions	
Internal programmable	An internal space of 16.5 KB is provided for 256 sequences, which can save a controller on some occasions
External I/O	3 external digital outputs (24V,0.5A),the target position to output or alarm output function can be implemented by internal programming8 external digital inputs, supporting internal sequence calling via the input interface and positioning function(input delay: about 1 ms; input current: about 4 mA)
Analog input	One differential analog input, implementing control over motor speed and position by analog input; input voltage range $\pm 10V$, input delay: about 0.1 ms
Analog output	Two independent analog outputs, capable of monitoring the change of internal object
Comparator	Four internal comparators, with the comparison results to be used to trigger program sequences
Timer	Supporting the function of triggering sequences by timer or events
Counter	Four groups of internal counters, which can be set to trigger sequences
Calculator	An internal calculator can be used for data duplication, addition, subtraction, multiplication, and division, and logic operation
Internal oscilloscope	The ECO2WIN software enables a user to monitor operation parameters such as speed, position and current on a PC
Encoder signal output function	In a master/slave control mode, the motor encoder signal or master encoder signal can be the input for the slave signal encoder, with a maximum output frequency of 2 MHz
Master encoder signal input function	Programmable to be pulse/direction signal control, CW/CCWW control, electronic gear or electronic cam control (5V signal), with a maximum input frequency of 2 MHz

Feed back signal 1	Incremental A, B, Z , /A, /B, /Z signal
RS232	9.6K baud rate, supporting a maximum of 15 sites, and supporting direct communication with a PC with the ECO2WIN software, or direct communication with an eView touch screen or text
RS485	38.4K baud rate, supporting a maximum of 15 sites, and communication cables with a length up to 400M
CAN BUS	Maximum baud rate of 1M, and supporting a maximum of 127 sites
PROFIBUS DP	Maximum baud rate of 12M, and supporting a maximum of 127 sites

[ED Servo System](#)