

## DRA-40-12



- Universal AC input / Full range
- Protections: Short Circuit / Overload / Over Voltage
- Can Be Installed on DIN rail TS-35/7.5 or 15
- Output Voltage Adjustable Through Internal Potentiometer
- Output Current Adjustable Through External 1~10Vdc, PWM Signal Or Resistance
- Cooling By Free Air Convection
- Pass LPS
- LED Indicator For Power On
- 100% Full Load Burn-In Test
- 3 Years Warranty

?????????: ??? ?????????????? ?????

**Price**

Sales price without tax 28,80 €

[?????? ?? ? ? ??????](#)

Manufacturer [??????????????: Mean Well](#)

Description	SPECIFICATION	
	MODEL	DRA-40-12
OUTPUT	DC VOLTAGE	12V
	CONSTANT CURRENT REGION	3~12V
	RATED CURRENT	3.34A
	CURRENT RANGE	0 ~ 3.34A
	RATED POWER	40.08W
	RIPPLE & NOISE (max.) Note.2	120mVp-p
	VOLTAGE ADJ.	12 ~ 15V

	<b>RANGE</b>	
	<b>VOLTAGE TOLERANCE</b> <b>Note.3</b>	±1.0%
	<b>LINE REGULATION</b>	±0.5%
	<b>LOAD REGULATION</b>	±0.5%
	<b>SETUP, RISE TIME</b> <b>Note.4</b>	400ms, 90ms/230V AC  800ms, 90ms/115V AC At Full Load
	<b>HOLD UP TIME (Typ.)</b>	50ms/230V AC  10ms/115V AC At Full Load
<b>INPUT</b>	<b>VOLTAGE RANGE</b>	90 ~ 264VAC  127 ~ 370VDC [DC Input Operation Possible By Connecting AC/L(+), AC/N(-)]
	<b>FREQUENCY RANGE</b>	47 ~ 63Hz
	<b>EFFICIENCY (Typ.)</b>	85%
	<b>AC CURRENT (Typ.)</b>	0.8A/115V AC  0.6A/230V AC
	<b>INRUSH CURRENT (Typ.)</b>	COLD START 30A/115VAC 60A/230VAC
<b>PROTECTION</b>	<b>OVERLOAD</b>	95 ~ 108% Rated Output Power  Protection Type : Constant Current Limiting, Recovers Automatically After Fault Condition Is

		Removed
	<b>OVER VOLTAGE</b>	14.49 ~ 18.63V Protection Type : Shut Down O/P Voltage, Re-Power On To Recover
<b>ENVIRONMENT</b>	<b>WORKING TEMP.</b>	-30 ~ +70 °C (Refer To "Derating Curve")
	<b>WORKING HUMIDITY</b>	20 ~ 90% RH Non-Condensing
	<b>STORAGE TEMP., HUMIDITY</b>	-40 ~ +85°C, 10 ~ 95% RH
	<b>TEMP. COEFFICIENT</b>	± 0.03%/°C (0 ~ 55°C) On Output
	<b>VIBRATION</b>	10 ~ 500Hz, 2G 10min./1Cycle, 60min. Each Along X, Y, Z Axes
<b>SAFETY &amp; EMC (Note 5)</b>	<b>SAFETY STANDARDS</b>	UL60950-1, TUV EN60950-1 Approved
	<b>WITHSTANDING VOLTAGE</b>	I/P-O/P:3 KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC
	<b>ISOLATION RESISTANCE</b>	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C / 70% RH
	<b>EMC EMISSION</b>	Compliance to EN55032 (CISPR32) Class B, EN61000-3-2,-3
	<b>EMC IMMUNITY</b>	Compliance to EN61000-4-2, 3,4,5,6,8, 11, EN55024, EN61204-

		3, light industry level, criteria A
<b>OTHERS</b>	<b>MTBF</b>	439.3K hrs min. MIL-HDB K-217F (25°C)
	<b>DIMENSION</b>	40*90*100mm (W*H*D)
	<b>PACKING</b>	0.3Kg; 42 pcs/13.6Kg/0.82CU FT
<b>NOTE</b>	<p>1. All parameters NOT specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature.</p> <p>2. Ripple &amp; noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf &amp; 47uf parallel capacitor.</p> <p>3. Tolerance : Includes set up tolerance, line regulation and load regulation.</p> <p>4. Length of set up time is measured at cold first start. Turning ON/OFF the power supply may lead to increase of the set up time.</p> <p>5. The power supply is considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets EMC directives. For guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies." (as available on <a href="http://www.meanwell.com">http://www.meanwell.com</a>)</p> <p>6. Installation clearances : 40mm on top, 20mm on the bottom, 5mm on the left and right side are recommended when</p>	

loaded permanently with full power. In case the adjacent device is a heat source, 15mm clearance is recommended.
--

[DRA-40-12 Specification](#)